


Fiber Optic Distribution box -8 fiber - LC Duplex - Empty box without adapter and PLC or pigtail

MODEL: FODB-8F-LC-DX



Overview

- This distribution box terminates up to 2 fiber optic cables, offers spaces for splitters and up to 8 fusions, allocates 8 SC adapters and working under outdoor environments. It is a perfect cost-effective solution-provider in the FTTx networks.

Specifications

Dimensions and Capacity	
► Dimensions (H*W*D)	243mm*195mm*55mm
► Color	White
► Weight	0.56 kg
► Adapter Type	SC Simplex/LC Duplex
► Adapter Capacity	8 pcs
► Splitter Type	1*8 mini type splitter
► Number of Cable Entrance(s) and Exit(s)	2:8/3:8
► Cable inlet caliber	12mm
► Optional Accessories	Adapters, Pigtails, Heat Shrink Tubes, Micro Splitter
► Working Temperature	-40°C~+65°C

Fiber Optic Distribution box -8 fiber - LC Duplex - Empty box without adapter and PLC or pigtail

MODEL: FODB-8F-LC-DX

Shipping Information	
► Package Contents	Fiber optics distribution box, 1 unit; Keys for lock, 2 keys; Wall mount accessories, 1 set
► Package Dimensions(W*H*D)	248mm*205mm*60mm
► Material	Carton box
► Weight	0.6 kg

Structure and Features

- Splice and patch cord use Separation structure , easy to Capacity expansion and maintenance maintenance
- High quality plastic, Beautiful appearance appearance
- Internal turnover structure structure, easy to maintenance maintenance
- Can install 8 pcs of SC adapters adapters
- Can install mini type splitter splitter
- Could exit 8 pcs of drop cable cable
- Protection levels levels: IP6IP65

Installation Instructions

Installation preparation

- Checking the product Checking the product :As per the packing list to check it one by one.
- Documents Tools:

NO	Type	Tool's name
1	replacement tool	spanner, sleeve sleeve,bolt driver bolt driver, electric drill electric drill, small hammer and so on

Fiber-optical stripping and fix

- As per the requirement,open the hole hole-at the bottom of the box,then install the seal rings
- As per the cable size to cut seal rings, cable through the it
- Adjust the length of cable, keep extra cable around 0.5m 0.5m:

Fiber Optic Distribution box -8 fiber - LC Duplex - Empty box without adapter and PLC or pigtail


MODEL: FODB-8F-LC-DX

- Clean the cable, cut the cable protector around 0.4m, keep armoured part around 30mm, keep the fiber around 60mm.
- When strip the cable, use insulating tape or heat shrink protector
- Put the fiber through the hole, fix it with clamp, then tighten the screws.

Trunk Optical Cables and route with pigtail

- Strip the fiber and pigtail, 1.3m to 1.5m, then put tube protector.
- Open the tray, splice the fiber.
- Put the finished fiber into the tray.
- Fixed the fiber and pigtail.
- Remark the fiber and record it.

Mounting Size for reference



Ordering Information:

Model: FODB-8F-LC-DX

- FODB: Fiber Optic Distribution Box
- 8F denotes 8 fiber
- LC denotes Fiber Adapter Type
- DX denotes Duplex